

EXIDOR

# 24V POWER SUPPLY UNIT

Recommended for use with Exidor's electromagnetic door closers

## FEATURES

- 2 Amp (up to 15 E-mag door closers)
- 4 Amp (up to 30 E-mag door closers)
- Switchmode technology - for improved energy efficiency
- White powder coated
- Multiple cable entry
- Cable retention points



E-mag Door Closer

AVAILABLE  
IN EITHER  
2 AMP OR  
4 AMP

[www.exidor.co.uk](http://www.exidor.co.uk) | +44 (0)1543 578661 | [sales@exidor.co.uk](mailto:sales@exidor.co.uk)

Exidor Limited, Progress Drive, Cannock, Staffordshire, WS11 0JE England, UK

EXIDOR

# 24V POWER SUPPLY UNIT

## TECHNICAL SPECIFICATIONS

- Ideal for electromagnetic door closers
- Not for use with battery back-up, ensuring fail-safe mode for E-mag door closers
- Full current to load
- 24-26VDC REGULATED output
- LED Indicators for O/P, fault & mains
- Short circuit protection
- Fused output
- Back EMF protection



CODE	DIMENSION	DESCRIPTION	WEIGHT
PSU2	200x200x65 (mm)	2 Amp Power Supply Switchmode (4 outputs)	1.25kg (Boxed) / 1.05kg (Unboxed)
PSU4	200x200x65 (mm)	4 Amp Power Supply Switchmode (8 outputs)	1.3kg (Boxed) / 1.1kg (Unboxed)

## USE WITH EXIDOR ELECTROMAGNETIC DOOR CLOSERS

- 2 Amp unit can accommodate up to 15 closers
- 4 Amp unit can accommodate up to 30 closers

